Data Sheet

July 21, 2005

31/2 Digit LCD, Low Power Display, A/D Converter with Overrange Recovery

intercil

The Intersil ICL7136 is a high performance, low power $3^{1}/_{2}$ digit, A/D converter. Included are seven segment decoders, display drivers, a reference, and a clock. The ICL7136 is designed to interface with a liquid crystal display (LCD) and includes a multiplexed backplane drive.

The ICL7136 brings together a combination of high accuracy, versatility, and true economy. It features auto-zero to less than 10μ V, zero drift of less than 1μ V/^oC, input bias current of 10pA (Max), and rollover error of less than one count. True differential inputs and reference are useful in all systems, but give the designer an uncommon advantage when measuring load cells, strain gauges and other bridge type transducers. Finally, the true economy of single power supply operation, enables a high performance panel meter to be built with the addition of only 10 passive components and a display.

The ICL7136 is an improved version of the ICL7126, eliminating the overrange hangover and hysteresis effects, and should be used in its place in all applications. It can also be used as a plug-in replacement for the ICL7106 in a wide variety of applications, changing only the passive components.

Features

- First Reading Overrange Recovery in One Conversion
 Period
- Guaranteed Zero Reading for 0V Input on All Scales
- True Polarity at Zero for Precise Null Detection
- 1pA Typical Input Current
- True Differential Input and Reference, Direct Display Drive
 LCD ICL7136
- Low Noise Less Than 15μV_{P-P}
- On Chip Clock and Reference
- · No Additional Active Circuits Required
- Low Power Less Than 1mW
- · Surface Mount Package Available
- Drop-In Replacement for ICL7126, No Changes Needed
- · Pb-Free Plus Anneal Available (RoHS Compliant)

Ordering Information

PART NUMBER	TEMP. RANGE (°C)	PACKAGE	PKG. DWG. #
ICL7136CPL	0 to 70	40 Ld PDIP	E40.6
ICL7136CPLZ (Note 1)	0 to 70	40 Ld PDIP (Pb-free) (Note 2)	E40.6
ICL7136CM44	0 to 70	44 Ld MQFP	Q44.10x10
ICL7136CM44Z (Note 1)	0 to 70	44 Ld MQFP (Pb-free)	Q44.10x10
ICL7136CM44ZT (Note 1)	44 Ld MQFP (Pb-free)	Tape and Reel	Q44.10x10

NOTES:

- Intersil Pb-free plus anneal products employ special Pb-free material sets; molding compounds/die attach materials and 100% matte tin plate termination finish, which are RoHS compliant and compatible with both SnPb and Pb-free soldering operations. Intersil Pb-free products are MSL classified at Pb-free peak reflow temperatures that meet or exceed the Pb-free requirements of IPC/JEDEC J STD-020.
- 2. Pb-free PDIPs can be used for through hole wave solder processing only. They are not intended for use in Reflow solder processing applications.





Absolute Maximum Ratings

Supply Voltage
ICL7136, V+ to V15V
Analog Input Voltage (Either Input) (Note 1) V+ to V-
Reference Input Voltage (Either Input)
Clock Input
ICL7136 TEST to V+
Operating Conditions
Temperature Range 0°C to 70°C

Thermal Information

Thermal Resistance (Typical, Note 2)	θ_{JA} (°C/W)
PDIP Package*	50
MQFP Package	75
Maximum Junction Temperature	150°C
Maximum Storage Temperature Range65	^o C to 150°C
Maximum Lead Temperature (Soldering 10s)	300°C
(MQFP - Lead Tips Only)	

*Pb-free PDIPs can be used for through hole wave solder processing only. They are not intended for use in Reflow solder processing applications.

CAUTION: Stresses above those listed in "Absolute Maximum Ratings" may cause permanent damage to the device. This is a stress only rating and operation of the device at these or any other conditions above those indicated in the operational sections of this specification is not implied.

NOTES:

1. Input voltages may exceed the supply voltages provided the input current is limited to $\pm 100 \mu A.$

2. θ_{JA} is measured with the component mounted on a low effective thermal conductivity test board in free air. See Tech Brief TB379 for details.

Electrical Specifications (Note 3)

PARAMETER	TEST CONDITIONS		TYP	MAX	UNITS		
SYSTEM PERFORMANCE							
Zero Input Reading	V _{IN} = 0V, Full Scale = 200mV	-000.0	±000.0	+000.0	Digital Reading		
Ratiometric Reading	V _{IN} = V _{REF} , V _{REF} = 100mV	999	999/ 1000	1000	Digital Reading		
Rollover Error	$-V_{IN}$ = +V _{IN} \cong 200mV Difference in Reading for Equal Positive and Negative Inputs Near Full Scale	-	±0.2	±1	Counts		
Linearity	Full Scale = 200mV or Full Scale = 2V Maximum Deviation from Best Straight Line Fit (Note 5)	-	±0.2	±1	Counts		
Common Mode Rejection Ratio	V_{CM} = ±1V, V_{IN} = 0V, Full Scale = 200mV (Note 5)	-	50	-	μV/V		
Noise	V _{IN} = 0V, Full Scale = 200mV (Peak-To-Peak Value Not Exceeded 95% of Time) (Note 5)		15	-	μV		
Leakage Current Input	V _{IN} = 0V (Note 5)	-	1	10	pА		
Zero Reading Drift	V _{IN} = 0V, 0°C To 70°C (Note 5)	-	0.2	1	μV/°C		
Scale Factor Temperature Coefficient	V _{IN} = 199mV, 0°C To 70°C, (Ext. Ref. 0ppm/×°C) (Note 5)	-	1	5	ppm/°C		
COMMON Pin Analog Common Voltage	DMMON Pin Analog Common Voltage $25k\Omega$ Between Common and Positive Supply (With Respect to + Supply)		3.0	3.2	V		
Temperature Coefficient of Analog Common	$25k\Omega$ Between Common and Positive Supply (With Respect to + Supply) (Note 5)	-	150	-	ppm/°C		
SUPPLY CURRENT							
V+ Supply Current V _{IN} = 0 (Does Not Include Common Current) 16kHz Oscillator (Note 6)		-	70	100	μΑ		
DISPLAY DRIVER	DISPLAY DRIVER						
Peak-To-Peak Segment Drive Voltage and Peak-To-Peak Backplane Drive Voltage	V+ to V- = 9V (Note 4)	4	5.5	6	V		

NOTES:

3. Unless otherwise noted, specifications apply to the ICL7136 at $T_A = 25^{\circ}$ C, $f_{CLOCK} = 48$ kHz. ICL7136 is tested in the circuit of Figure 1.

4. Back plane drive is in phase with segment drive for "off" segment, 180 degrees out of phase for "on" segment. Frequency is 20 times conversion rate. Average DC component is less than 50mV.

5. Not tested, guaranteed by design.

6. 48kHz oscillator increases current by $20\mu A$ (Typ).

3

Typical Applications and Test Circuits



FIGURE 1. ICL7136 TEST CIRCUIT AND TYPICAL APPLICATION WITH LCD DISPLAY COMPONENTS SELECTED FOR 200mV FULL SCALE

Design Information Summary Sheet

OSCILLATOR FREQUENCY

 $\label{eq:fOSC} \begin{array}{l} f_{OSC} = 0.45/RC \\ C_{OSC} > 50 pF; \ R_{OSC} > 50 k\Omega \\ f_{OSC} \left(Typ \right) = 48 kHz \end{array}$

OSCILLATOR PERIOD

 $t_{OSC} = RC/0.45$

• INTEGRATION CLOCK FREQUENCY

 $f_{CLOCK} = f_{OSC}/4$

• INTEGRATION PERIOD

 $t_{INT} = 1000 \text{ x} (4/f_{OSC})$

- 60/50Hz REJECTION CRITERION t_{INT}/t_{60Hz} or t_{INT}/t_{50Hz} = Integer
- OPTIMUM INTEGRATION CURRENT $I_{INT} = 1 \mu A$
- FULL SCALE ANALOG INPUT VOLTAGE V_{INFS} (Typ) = 200mV or 2V
- INTEGRATE RESISTOR

 $\mathsf{R}_{\mathsf{INT}} = \frac{\mathsf{V}_{\mathsf{INFS}}}{\mathsf{I}_{\mathsf{INT}}}$

• INTEGRATE CAPACITOR

 $C_{INT} = \frac{(t_{INT})(I_{INT})}{V_{INT}}$

• INTEGRATOR OUTPUT VOLTAGE SWING

 $V_{INT} = \frac{(t_{INT})(I_{INT})}{C_{INT}}$

• VINT MAXIMUM SWING:

(V- + 0.5V) < V_{INT} < (V+ - 0.5V), V_{INT} (Typ) = 2V

Typical Integrator Amplifier Output Waveform (INT Pin)



TOTAL CONVERSION TIME = 4000 x t_{CLOCK} = 16,000 x t_{OSC}

DISPLAY COUNT

 $COUNT = 1000 \times \frac{V_{IN}}{V_{REF}}$

CONVERSION CYCLE

 $t_{CYC} = t_{CL0CK} \times 4000$ $t_{CYC} = t_{OSC} \times 16,000$ when f_{OSC} = 48kHz; t_{CYC} = 333ms

COMMON MODE INPUT VOLTAGE

 $(V- + 1V) < V_{IN} < (V+ - 0.5V)$

AUTO-ZERO CAPACITOR

0.01μF < C_{AZ} < 1μF

- REFERENCE CAPACITOR
- 0.1μF < C_{REF} < 1μF
- V_{СОМ}

Biased between V+ and V-.

• $V_{COM} \cong V+ - 2.8V$

Regulation lost when V+ to V- < \cong 6.8V. If V_{COM} is externally pulled down to (V + to V -)/2, the V_{COM} circuit will turn off.

• POWER SUPPLY: SINGLE 9V

V+ - V- = 9V Digital supply is generated internally V_{TEST} \cong V+ - 4.5V

• DISPLAY: LCD

Type: Direct drive with digital logic supply amplitude.

Pin Descriptions

44 PIN OP FLATPACK NAME FUNCTION DESCRIPTION 1 8 V+ Supply Power Supply: 2 9 D1 Output Driver Pin for Segment "D" of the display units digit. 3 100 C1 Output Driver Pin for Segment "B" of the display units digit. 4 11 B1 Output Driver Pin for Segment "B" of the display units digit. 5 12 A1 Output Driver Pin for Segment "B" of the display units digit. 6 13 F1 Output Driver Pin for Segment "B" of the display units digit. 7 14 G1 Output Driver Pin for Segment "D" of the display units digit. 9 16 D2 Output Driver Pin for Segment "D" of the display tens digit. 11 18 B2 Output Driver Pin for Segment "E" of the display tens digit. 12 19 A2 Output Driver Pin for Segment "E" of the display tens digit. 14 21 E2 Output Driver Pin for Segment "E" of the display hundreds digit. <td< th=""><th colspan="2">PIN NUMBER</th><th></th><th></th><th></th></td<>	PIN NUMBER				
Image: Plance in the image in the		44 PIN	-		
1 8 V+ Supply. Power Supply. 2 9 D1 Output Driver Pin for Segment "D" of the display units digit. 3 10 C1 Output Driver Pin for Segment "C" of the display units digit. 4 11 B1 Output Driver Pin for Segment "C" of the display units digit. 6 13 F1 Output Driver Pin for Segment "C" of the display units digit. 7 14 G1 Output Driver Pin for Segment "C" of the display units digit. 9 16 D2 Output Driver Pin for Segment "C" of the display units digit. 10 17 C2 Output Driver Pin for Segment "C" of the display tens digit. 11 18 B2 Output Driver Pin for Segment "E" of the display tens digit. 13 20 F2 Output Driver Pin for Segment "E" of the display tens digit. 14 21 E2 Output Driver pin for segment "E" of the display hundreds digit. 16 23 B3 Output Driver pin for segment "E" of the display hundreds digit.	40 PIN DIP	FLATPACK	NAME	FUNCTION	DESCRIPTION
2 9 D1 Output Driver Pin for Segment 'C' of the display units digit. 3 10 C1 Output Driver Pin for Segment 'C' of the display units digit. 4 11 B1 Output Driver Pin for Segment 'C' of the display units digit. 5 12 A1 Output Driver Pin for Segment 'C' of the display units digit. 6 13 F1 Output Driver Pin for Segment 'C' of the display units digit. 7 14 G1 Output Driver Pin for Segment 'C' of the display tens digit. 9 16 D2 Output Driver Pin for Segment 'C' of the display tens digit. 11 18 B2 Output Driver Pin for Segment 'C' of the display tens digit. 12 19 A2 Output Driver Pin for Segment 'E' of the display tens digit. 13 20 F2 Output Driver Pin for Segment 'E' of the display tens digit. 14 21 E2 D3 Output Driver pin for segment 'E' of the display hundreds digit. 16 23 B3 Output Driv	1	8	V+	Supply	Power Supply.
3 10 C1 Output Driver Pin for Segment "G" of the display units digit. 4 11 B1 Output Driver Pin for Segment "A" of the display units digit. 6 13 F1 Output Driver Pin for Segment "G" of the display units digit. 7 14 G1 Output Driver Pin for Segment "G" of the display units digit. 8 15 E1 Output Driver Pin for Segment "G" of the display tens digit. 9 16 D2 Output Driver Pin for Segment "G" of the display tens digit. 10 17 C2 Output Driver Pin for Segment "G" of the display tens digit. 11 18 B2 Output Driver Pin for Segment "F" of the display tens digit. 13 20 F2 Output Driver pin for Segment "F" of the display hundreds digit. 14 21 E2 Output Driver pin for Segment "F" of the display hundreds digit. 16 23 B3 Output Driver pin for Segment "F" of the display hundreds digit. 17 24 F3 Output Driver pin for	2	9	D1	Output	Driver Pin for Segment "D" of the display units digit.
4 11 B1 Output Driver Pin for Segment "A" of the display units digit. 5 12 A1 Output Driver Pin for Segment "A" of the display units digit. 6 13 F1 Output Driver Pin for Segment "C" of the display units digit. 7 14 G1 Output Driver Pin for Segment "C" of the display units digit. 9 16 D2 Output Driver Pin for Segment "C" of the display tens digit. 10 17 C2 Output Driver Pin for Segment "C" of the display tens digit. 12 19 A2 Output Driver Pin for Segment "F" of the display tens digit. 13 20 F2 Output Driver Pin for Segment "F" of the display tens digit. 14 21 E2 Output Driver Pin for segment "F" of the display hundreds digit. 16 23 B3 Output Driver pin for segment "F" of the display hundreds digit. 17 24 F3 Output Driver pin for segment "F" of the display hundreds digit. 19 26 AB4 Output Driver pin fo	3	10	C1	Output	Driver Pin for Segment "C" of the display units digit.
5 12 A1 Output Driver Pin for Segment "A" of the display units digit. 6 13 F1 Output Driver Pin for Segment "G" of the display units digit. 7 14 G1 Output Driver Pin for Segment "G" of the display units digit. 9 16 D2 Output Driver Pin for Segment "G" of the display units digit. 10 17 C2 Output Driver Pin for Segment "G" of the display tens digit. 11 18 B2 Output Driver Pin for Segment "G" of the display tens digit. 12 19 A2 Output Driver Pin for Segment "G" of the display tens digit. 13 20 F2 Output Driver Pin for Segment "G" of the display tens digit. 14 21 E2 Output Driver Pin for segment "G" of the display hundreds digit. 16 23 B3 Output Driver Pin for segment "G" of the display hundreds digit. 17 24 F3 Output Driver pin for segment "G" of the display hundreds digit. 19 26 AB4 Output Driver pin f	4	11	B1	Output	Driver Pin for Segment "B" of the display units digit.
6 13 F1 Output Driver Pin for Segment "F" of the display units digit. 7 14 G1 Output Driver Pin for Segment "G" of the display units digit. 9 16 D2 Output Driver Pin for Segment "C" of the display units digit. 10 17 C2 Output Driver Pin for Segment "C" of the display tens digit. 11 18 B2 Output Driver Pin for Segment "F" of the display tens digit. 12 19 A2 Output Driver Pin for Segment "F" of the display tens digit. 13 20 F2 Output Driver Pin for Segment "F" of the display tens digit. 14 21 E2 D3 Output Driver pin for segment "F" of the display hundreds digit. 16 23 B3 Output Driver pin for segment "F" of the display hundreds digit. 19 26 AB4 Output Driver pin for segment "G" of the display hundreds digit. 20 27 POL Output Driver pin for segment "G" of the display hundreds digit. 21 28 BP/GND Output<	5	12	A1	Output	Driver Pin for Segment "A" of the display units digit.
7 14 G1 Output Driver Pin for Segment "G" of the display units digit. 8 15 E1 Output Driver Pin for Segment "G" of the display units digit. 9 16 D2 Output Driver Pin for Segment "G" of the display tens digit. 10 17 C2 Output Driver Pin for Segment "G" of the display tens digit. 11 18 B2 Output Driver Pin for Segment "G" of the display tens digit. 12 19 A2 Output Driver Pin for Segment "G" of the display tens digit. 13 20 F2 Output Driver Pin for Segment "G" of the display tens digit. 14 21 E2 Output Driver pin for segment "G" of the display hundreds digit. 16 23 B3 Output Driver pin for segment "F" of the display hundreds digit. 17 24 F3 Output Driver pin for bed mained sign. 18 25 E3 Output Driver pin for bed mained sign. 20 27 POL Output Driver pin for segment "A" of the display hundreds digit. <td>6</td> <td>13</td> <td>F1</td> <td>Output</td> <td>Driver Pin for Segment "F" of the display units digit.</td>	6	13	F1	Output	Driver Pin for Segment "F" of the display units digit.
8 15 E1 Output Driver Pin for Segment "E" of the display units digit. 9 16 D2 Output Driver Pin for Segment "D" of the display tens digit. 10 17 C2 Output Driver Pin for Segment "B" of the display tens digit. 11 18 B2 Output Driver Pin for Segment "B" of the display tens digit. 13 20 F2 Output Driver Pin for Segment "F" of the display tens digit. 14 21 E2 Output Driver Pin for Segment "F" of the display tens digit. 16 23 B3 Output Driver pin for segment "F" of the display hundreds digit. 17 24 F3 Output Driver pin for segment "F" of the display hundreds digit. 18 25 E3 Output Driver pin for segment "B" of the display hundreds digit. 20 27 POL Output Driver pin for segment "C" of the display hundreds digit. 21 28 BP/GND Output Driver pin for segment "C" of the display hundreds digit. 24 31 C3 Output D	7	14	G1	Output	Driver Pin for Segment "G" of the display units digit.
9 16 D2 Output Driver Pin for Segment "D" of the display tens digit. 10 17 C2 Output Driver Pin for Segment "B" of the display tens digit. 11 18 B2 Output Driver Pin for Segment "B" of the display tens digit. 12 19 A2 Output Driver Pin for Segment "B" of the display tens digit. 14 20 F2 Output Driver Pin for Segment "B" of the display tens digit. 16 23 B3 Output Driver Pin for segment "B" of the display hundreds digit. 17 24 F3 Output Driver pin for segment "E" of the display hundreds digit. 18 25 E3 Output Driver pin for segment "E" of the display hundreds digit. 20 27 POL Output Driver pin for segment "E" of the display hundreds digit. 23 30 A3 Output Driver pin for segment "C" of the display hundreds digit. 24 31 C3 Output Driver pin for segment "C" of the display hundreds digit. 25 32 G2 Output D	8	15	E1	Output	Driver Pin for Segment "E" of the display units digit.
1017C2OutputDriver Pin for Segment "C" of the display tens digit.1118B2OutputDriver Pin for Segment "B" of the display tens digit.1219A2OutputDriver Pin for Segment "F" of the display tens digit.1320F2OutputDriver Pin for Segment "E" of the display tens digit.1421E2D3OutputDriver pin for segment "E" of the display hundreds digit.1623B3OutputDriver pin for segment "E" of the display hundreds digit.1724F3OutputDriver pin for segment "E" of the display hundreds digit.1825E3OutputDriver pin for segment "E" of the display hundreds digit.2027POLOutputDriver pin for bot "A" and "B" segments of the display.2128BP/GNDOutputDriver pin for the LCD backplane/Power Supply Ground.2229G3OutputDriver pin for segment "C" of the display hundreds digit.2431C3OutputDriver pin for segment "C" of the display hundreds digit.2532G2OutputDriver pin for segment "C" of the display hundreds digit.2634V'SupplyNegative power supply.2735INTOutputDriver pin for segment "C" of the display hundreds digit.2836BUFFOutputDriver pin for segment "C" of the display hundreds digit.2937A-ZInputIntegrator amplifier output. To be connected to int	9	16	D2	Output	Driver Pin for Segment "D" of the display tens digit.
1118B2OutputDriver Pin for Segment "B" of the display tens digit.1219A2OutputDriver Pin for Segment "F" of the display tens digit.1320F2OutputDriver Pin for Segment "F" of the display tens digit.1421E2OutputDriver Pin for Segment "E" of the display tens digit.1623B3OutputDriver pin for segment "F" of the display hundreds digit.1724F3OutputDriver pin for segment "E" of the display hundreds digit.1825E3OutputDriver pin for segment "E" of the display hundreds digit.2027POLOutputDriver pin for segment "E" of the display hundreds digit.2128BP/GNDOutputDriver pin for bengment "E" of the display.2128BP/GNDOutputDriver pin for segment "G" of the display hundreds digit.2330A3OutputDriver pin for segment "G" of the display hundreds digit.2431C3OutputDriver pin for segment "G" of the display hundreds digit.2532G2OutputDriver pin for segment "G" of the display hundreds digit.2634VSupplyNegative power supply.2735INTOutputIntegrator amplifier output. To be connected to integrating capacitor.2836BUFFOutputIntegrator amplifier output. To be connected to integrating resistor.2937A-ZInputIntegrator amplifier output. To be connect	10	17	C2	Output	Driver Pin for Segment "C" of the display tens digit.
1219A2OutputDriver Pin for Segment "A" of the display tens digit.1320F2OutputDriver Pin for Segment "E" of the display tens digit.1421EZOutputDriver Pin for Segment "E" of the display tens digit.1522D3OutputDriver pin for segment "E" of the display hundreds digit.1623B3OutputDriver pin for segment "E" of the display hundreds digit.1724F3OutputDriver pin for segment "E" of the display hundreds digit.1825E3OutputDriver pin for begment "E" of the display hundreds digit.2027POLOutputDriver pin for the negative sign of the display hundreds digit.2128BP/GNDOutputDriver pin for the negative sign of the display hundreds digit.2330A3OutputDriver pin for segment "G" of the display hundreds digit.2431C3OutputDriver pin for segment "G" of the display hundreds digit.2532G2OutputDriver pin for segment "G" of the display hundreds digit.2634VSupplyNegative power supply.2735INTOutputIntegrator amplifier output. To be connected to integrating capacitor.2836BUFFOutputIntegrator amplifier output. To be connected to anto-zero capacitor.3038IN LOInputIntegrator amplifier output. To be connected to integrating resistor.3139IN HIComection pins	11	18	B2	Output	Driver Pin for Segment "B" of the display tens digit.
1320F2OutputDriver Pin for Segment "E" of the display tens digit.1421E2OutputDriver Pin for Segment "E" of the display tens digit.1522D3OutputDriver pin for segment "D" of the display hundreds digit.1623B3OutputDriver pin for segment "E" of the display hundreds digit.1724F3OutputDriver pin for segment "E" of the display hundreds digit.1825E3OutputDriver pin for segment "E" of the display hundreds digit.2027POLOutputDriver pin for segment "E" of the display hundreds digit.2128BP/GNDOutputDriver pin for the negative sign of the display hundreds digit.2330A3OutputDriver pin for segment "G" of the display hundreds digit.2431C3OutputDriver pin for segment "G" of the display hundreds digit.2532G2OutputDriver pin for segment "G" of the display hundreds digit.2634VSupplyNegative power supply.2735INTOutputDriver pin for segment "G" of the display hundreds digit.2836BUFFOutputIntegrator amplifier output. To be connected to integrating capacitor.3038IN LOInputIntegrator amplifier input. To be connected to integrating capacitor.3038IN LOInputDifferential inputs. To be connected to integrating capacitor.3139IN HIInputDiffere	12	19	A2	Output	Driver Pin for Segment "A" of the display tens digit.
1421E2OutputDriver Pin for Segment "E" of the display tens digit.1522D3OutputDriver pin for segment "D" of the display hundreds digit.1623B3OutputDriver pin for segment "E" of the display hundreds digit.1724F3OutputDriver pin for segment "E" of the display hundreds digit.1825E3OutputDriver pin for segment "E" of the display hundreds digit.1926AB4OutputDriver pin for both "A" and "B" segments of the display thousands digit.2027POLOutputDriver pin for the negative sign of the display hundreds digit.2128BP/GNDOutputDriver pin for the LCD backplane/Power Supply Ground.2229G3OutputDriver pin for segment "G" of the display hundreds digit.2330A3OutputDriver pin for segment "G" of the display hundreds digit.2431C3OutputDriver pin for segment "G" of the display hundreds digit.2532G2OutputDriver pin for segment "G" of the display hundreds digit.2634V"SupplyNegative power supply.2735INTOutputIntegrator amplifier output. To be connected to integrating capacitor.2836BUFFOutputIntegrator amplifier input. To be connected to input voltage to be measured. LO and HI3139IN HIInputDifferential inputs. To be connected to input voltage to be measured. LO and HI33<	13	20	F2	Output	Driver Pin for Segment "F" of the display tens digit.
1522D3OutputDriver pin for segment "D" of the display hundreds digit.1623B3OutputDriver pin for segment "E" of the display hundreds digit.1724F3OutputDriver pin for segment "E" of the display hundreds digit.1825E3OutputDriver pin for segment "E" of the display hundreds digit.1926AB4OutputDriver pin for segment "E" of the display hundreds digit.2027POLOutputDriver pin for the negative sign of the display hundreds digit.2128BP/GNDOutputDriver pin for segment "G" of the display hundreds digit.2330A3OutputDriver pin for segment "G" of the display hundreds digit.2431C3OutputDriver pin for segment "G" of the display hundreds digit.2532G2OutputDriver pin for segment "G" of the display hundreds digit.2634VSupplyNegative power supply.2735INTOutputIntegrator amplifier output. To be connected to integrating capacitor.2836BUFFOutputInput buffer amplifier output. To be connected to integrating resistor.3038IN LOInput buffer amplifier input. To be connected to integrating resistor.3341CREF"Common Supply/3442CREF"Connection pins for reference and do not imply that LO should be connected to lower potential, e.g., for negative inputs IN LO has a higher potential than IN HI.3240 <td>14</td> <td>21</td> <td>E2</td> <td>Output</td> <td>Driver Pin for Segment "E" of the display tens digit.</td>	14	21	E2	Output	Driver Pin for Segment "E" of the display tens digit.
1623B3OutputDriver pin for segment "B" of the display hundreds digit.1724F3OutputDriver pin for segment "E" of the display hundreds digit.1825E3OutputDriver pin for segment "E" of the display hundreds digit.1926AB4OutputDriver pin for segment "E" of the display hundreds digit.2027POLOutputDriver pin for both "A" and "B" segments of the display thousands digit.2128BP/GNDOutputDriver pin for both "A" and "B" segments dit display hundreds digit.2330A3OutputDriver pin for segment "A" of the display hundreds digit.2431C3OutputDriver pin for segment "C" of the display hundreds digit.2532G2OutputDriver pin for segment "G" of the display hundreds digit.2634V"SupplyNegative power supply.2735INTOutputIntegrator amplifier output. To be connected to integrating capacitor.2836BUFFOutputIntegrator amplifier input. To be connected to integrating resistor.3038IN LOInputDifferential inputs. To be connected to inmut voltage to be measured. LO and HI3139IN HICREF"Connection pins for reference and do not imply that LO should be connected to lower potential e.g., for negative inputs IN LO has a higher potential than IN HI.3240COMMONSupply/ OutputInternal voltage reference output.3341C_REF" C_REF"	15	22	D3	Output	Driver pin for segment "D" of the display hundreds digit.
1724F3OutputDriver pin for segment "F" of the display hundreds digit.1825E3OutputDriver pin for segment "E" of the display hundreds digit.1926AB4OutputDriver pin for both "A" and "B" segments of the display hundreds digit.2027POLOutputDriver pin for both "A" and "B" segments of the display.2128BP/GNDOutputDriver pin for the negative sign of the display hundreds digit.2330A3OutputDriver pin for segment "G" of the display hundreds digit.2431C3OutputDriver pin for segment "C" of the display hundreds digit.2532G2OutputDriver pin for segment "G" of the display hundreds digit.2634VSupplyNegative power supply.2735INTOutputIntegrator amplifier output. To be connected to integrating capacitor.2836BUFFOutputIntegrator amplifier output. To be connected to integrating resistor.2937A-ZInputIntegrator amplifier output. To be connected to integrating resistor.3038IN LOInputDifferential inputs. To be connected to input youtput to be measured. LO and HI3139IN HICommonConnection pins for reference and do not imply that LO should be connected to lower potential, e.g., for negative inputs IN LO as a higher potential than IN HI.3240COMMONSupply/Input pins for reference voltage to the device. REF HI should be positive reference to REF LO </td <td>16</td> <td>23</td> <td>B3</td> <td>Output</td> <td>Driver pin for segment "B" of the display hundreds digit.</td>	16	23	B3	Output	Driver pin for segment "B" of the display hundreds digit.
1825E3OutputDriver pin for segment "E" of the display hundreds digit.1926AB4OutputDriver pin for both "A" and "B" segments of the display thousands digit.2027POLOutputDriver pin for the negative sign of the display.2128BP/GNDOutputDriver pin for the LCD backplane/Power Supply Ground.2229G3OutputDriver pin for segment "G" of the display hundreds digit.2330A3OutputDriver pin for segment "G" of the display hundreds digit.2431C3OutputDriver pin for segment "G" of the display hundreds digit.2532G2OutputDriver pin for segment "G" of the display hundreds digit.2634VSupplyNegative power supply.2735INTOutputIntegrator amplifier output. To be connected to integrating capacitor.2836BUFFOutputIntegrator amplifier output. To be connected to auto-zero capacitor.3038IN LOInputInfegrator amplifier input. To be connected to auto-zero capacitor.3139IN HIInputInfegrator amplifier input. To be connected to anter potential than IN HI.3240COMMONSupply/ OutputInternal voltage reference output.3341CREF"Connection pins for reference capacitor.3442CREF+Connection pins for reference voltage to the device. REF HI should be positive reference to REF LO.373TESTInp	17	24	F3	Output	Driver pin for segment "F" of the display hundreds digit.
1926AB4OutputDriver pin for both "A" and "B" segments of the display thousands digit.2027POLOutputDriver pin for the negative sign of the display.2128BP/GNDOutputDriver pin for the LCD backplane/Power Supply Ground.2229G3OutputDriver pin for segment "G" of the display hundreds digit.2330A3OutputDriver pin for segment "G" of the display hundreds digit.2431C3OutputDriver pin for segment "G" of the display hundreds digit.2532G2OutputDriver pin for segment "G" of the display tens digit.2634V'SupplyNegative power supply.2735INTOutputIntegrator amplifier output. To be connected to integrating capacitor.2836BUFFOutputIntegrator amplifier input. To be connected to anto-zero capacitor.3038IN LOInputDifferential inputs. To be connected to input voltage to be measured. LO and HI3139IN HIInputDifferential inputs. To be connected to input voltage to be measured. LO and HI3341CREF- CREF+Connection pins for reference output.3341CREF- CREF+Connection pins for reference output.3341CREF- CREF+Connection pins for reference voltage to the device. REF HI should be positive reference to REF LO.3643REF LOInputInput pins for reference voltage to the device. REF HI should be positive reference to 	18	25	E3	Output	Driver pin for segment "E" of the display hundreds digit.
2027POLOutputDriver pin for the negative sign of the display.2128BP/GNDOutputDriver pin for the LCD backplane/Power Supply Ground.2229G3OutputDriver pin for segment "G" of the display hundreds digit.2330A3OutputDriver pin for segment "G" of the display hundreds digit.2431C3OutputDriver pin for segment "G" of the display hundreds digit.2532G2OutputDriver pin for segment "G" of the display to the display the display to the display the display to the	19	26	AB4	Output	Driver pin for both "A" and "B" segments of the display thousands digit.
2128BP/GNDOutputDriver pin for the LCD backplane/Power Supply Ground.2229G3OutputDriver pin for segment "G" of the display hundreds digit.2330A3OutputDriver pin for segment "A" of the display hundreds digit.2431C3OutputDriver pin for segment "G" of the display hundreds digit.2532G2OutputDriver pin for segment "G" of the display hundreds digit.2634V'SupplyNegative power supply.2735INTOutputIntegrator amplifier output. To be connected to integrating capacitor.2836BUFFOutputInput buffer amplifier output. To be connected to integrating resistor.2937A-ZInputIntegrator amplifier input. To be connected to auto-zero capacitor.3038IN LOInputDifferential inputs. To be connected to integrating resistor.3139IN HIIntegrator amplifier output. To be connected to auto-zero capacitor.3341CREF+Connection pins for reference and do not imply that LO should be connected to lower potential, e.g., for negative inputs IN LO has a higher potential than IN HI.3341CREF+Connection pins for reference capacitor.3442CREF+Connection pins for reference voltage to the device. REF HI should be positive reference to REF LO.373TESTInputDisplay test. Turns on all segments when tied to V+.384OSC3OutputDevice clock generator circuit connec	20	27	POL	Output	Driver pin for the negative sign of the display.
2229G3OutputDriver pin for segment "G" of the display hundreds digit.2330A3OutputDriver pin for segment "A" of the display hundreds digit.2431C3OutputDriver pin for segment "G" of the display hundreds digit.2532G2OutputDriver pin for segment "G" of the display hundreds digit.2634VSupplyNegative power supply.2735INTOutputIntegrator amplifier output. To be connected to integrating capacitor.2836BUFFOutputInput buffer amplifier output. To be connected to integrating resistor.2937A-ZInputIntegrator amplifier input. To be connected to integrating resistor.3038IN LOInputDifferential inputs. To be connected to integrat be connected to lower potential, e.g., for negative inputs IN LO has a higher potential than IN HI.3139IN HIComMONSupply/ OutputInternal voltage reference output.3341C _{REF} - C _{REF} +Connection pins for reference capacitor.3543REF LO REF HIInput pins for reference voltage to the device. REF HI should be positive reference to REF LO.373TESTInput Display test. Turns on all segments when tied to V+.384OSC3 OutputOutput407OSC1 DuputDevice clock generator circuit connection pins.	21	28	BP/GND	Output	Driver pin for the LCD backplane/Power Supply Ground.
23 30 A3 Output Driver pin for segment "A" of the display hundreds digit. 24 31 C3 Output Driver pin for segment "C" of the display hundreds digit. 25 32 G2 Output Driver pin for segment "G" of the display tens digit. 26 34 V Supply Negative power supply. 27 35 INT Output Integrator amplifier output. To be connected to integrating capacitor. 28 36 BUFF Output Input buffer amplifier output. To be connected to auto-zero capacitor. 30 38 IN LO Input Integrator amplifier input. To be connected to auto-zero capacitor. 30 38 IN LO Input Integrator amplifier output. To be connected to auto-zero capacitor. 31 39 IN HI Input Differential inputs. To be connected to intury ottage to be measured. LO and HI designators are for reference and do not imply that LO should be connected to lower potential, e.g., for negative inputs IN LO has a higher potential than IN HI. 32 40 COMMON Supply/ Output Connection pins for reference output. 33 41 C _{REF} - C _{REF} + Connection pins for reference voltage to the device. REF HI should be positi	22	29	G3	Output	Driver pin for segment "G" of the display hundreds digit.
2431C3OutputDriver pin for segment "C" of the display hundreds digit.2532G2OutputDriver pin for segment "G" of the display tens digit.2634V"SupplyNegative power supply.2735INTOutputIntegrator amplifier output. To be connected to integrating capacitor.2836BUFFOutputInput buffer amplifier output. To be connected to integrating resistor.2937A-ZInputIntegrator amplifier input. To be connected to auto-zero capacitor.3038IN LOInputDifferential inputs. To be connected to integrating resistor.3139IN HIInputDifferential inputs. To be connected to input voltage to be measured. LO and HI designators are for reference and do not imply that LO should be connected to lower potential, e.g., for negative inputs IN LO has a higher potential than IN HI.3240COMMONSupply/ OutputInternal voltage reference output.3341CREF* CREF+Connection pins for reference capacitor.3442CREF+InputInput pins for reference voltage to the device. REF HI should be positive reference to REF LO.373TESTInputDisplay test. Turns on all segments when tied to V+.384OSC3OutputDevice clock generator circuit connection pins.407OSC1InputInput	23	30	A3	Output	Driver pin for segment "A" of the display hundreds digit.
2532G2OutputDriver pin for segment "G" of the display tens digit.2634VSupplyNegative power supply.2735INTOutputIntegrator amplifier output. To be connected to integrating capacitor.2836BUFFOutputInput buffer amplifier output. To be connected to integrating resistor.2937A-ZInputIntegrator amplifier input. To be connected to auto-zero capacitor.3038IN LOInputDifferential inputs. To be connected to input voltage to be measured. LO and HI designators are for reference and do not imply that LO should be connected to lower potential, e.g., for negative inputs IN LO has a higher potential than IN HI.3240COMMONSupply/ OutputInternal voltage reference output.3341C _{REF*} Connection pins for reference capacitor.3543REF LO REF HIInputInput pins for reference voltage to the device. REF HI should be positive reference to REF LO.373TESTInputDisplay test. Turns on all segments when tied to V+.384OSC2 OSC1OutputDevice clock generator circuit connection pins.	24	31	C3	Output	Driver pin for segment "C" of the display hundreds digit.
2634VSupplyNegative power supply.2735INTOutputIntegrator amplifier output. To be connected to integrating capacitor.2836BUFFOutputInput buffer amplifier output. To be connected to integrating resistor.2937A-ZInputIntegrator amplifier input. To be connected to auto-zero capacitor.3038IN LOInputDifferential inputs. To be connected to input voltage to be measured. LO and HI3139IN HIDifferential inputs. To be connected to onto imply that LO should be connected to lower potential, e.g., for negative inputs IN LO has a higher potential than IN HI.3240COMMONSupply/ OutputInternal voltage reference output.3341CREF*Connection pins for reference capacitor.3442CREF*Connection pins for reference voltage to the device. REF HI should be positive reference to REF LO.373TESTInputDisplay test. Turns on all segments when tied to V+.384OSC3OutputDevice clock generator circuit connection pins.407OSC1InputInput	25	32	G2	Output	Driver pin for segment "G" of the display tens digit.
2735INTOutputIntegrator amplifier output. To be connected to integrating capacitor.2836BUFFOutputInput buffer amplifier output. To be connected to integrating resistor.2937A-ZInputIntegrator amplifier input. To be connected to auto-zero capacitor.3038IN LOInputDifferential inputs. To be connected to input voltage to be measured. LO and HI designators are for reference and do not imply that LO should be connected to lower potential, e.g., for negative inputs IN LO has a higher potential than IN HI.3240COMMONSupply/ OutputInternal voltage reference output.3341C _{REF} - C _{REF} +Connection pins for reference capacitor.3543REF LO REF HIInput pins for reference voltage to the device. REF HI should be positive reference to REF LO.373TESTInputDisplay test. Turns on all segments when tied to V+.384OSC3OutputDevice clock generator circuit connection pins.407OSC1InputInput	26	34	V-	Supply	Negative power supply.
2836BUFFOutputInput buffer amplifier output. To be connected to integrating resistor.2937A-ZInputIntegrator amplifier input. To be connected to auto-zero capacitor.3038IN LOInputDifferential inputs. To be connected to input voltage to be measured. LO and HI3139IN HIInputDifferential inputs. To be connected to input voltage to be measured. LO and HI3240COMMONSupply/ OutputInternal voltage reference and do not imply that LO should be connected to lower potential, e.g., for negative inputs IN LO has a higher potential than IN HI.3341CREF- CREF+Connection pins for reference output.3442CREF+Connection pins for reference capacitor.3543REF LO REF HIInputInput pins for reference voltage to the device. REF HI should be positive reference to REF LO.373TESTInputDisplay test. Turns on all segments when tied to V+.384OSC3 OutputOutputDevice clock generator circuit connection pins.407OSC1 InputInputDevice clock generator circuit connection pins.	27	35	INT	Output	Integrator amplifier output. To be connected to integrating capacitor.
2937A-ZInputIntegrator amplifier input. To be connected to auto-zero capacitor.3038IN LOInputDifferential inputs. To be connected to input voltage to be measured. LO and HI designators are for reference and do not imply that LO should be connected to lower potential, e.g., for negative inputs IN LO has a higher potential than IN HI.3240COMMONSupply/ OutputInternal voltage reference output.3341CREF- CREF+Connection pins for reference capacitor.3442CREF+Connection pins for reference voltage to the device. REF HI should be positive reference to REF LO.3644REF HIInput384OSC3Output396OSC2Output407OSC1Input	28	36	BUFF	Output	Input buffer amplifier output. To be connected to integrating resistor.
3038IN LOInputDifferential inputs. To be connected to input voltage to be measured. LO and HI designators are for reference and do not imply that LO should be connected to lower potential, e.g., for negative inputs IN LO has a higher potential than IN HI.3240COMMONSupply/ OutputInternal voltage reference output.3341C_REF*Connection pins for reference capacitor.3442C_REF+Connection pins for reference voltage to the device. REF HI should be positive reference to REF LO.373TESTInputDisplay test. Turns on all segments when tied to V+.384OSC3OutputDevice clock generator circuit connection pins.396OSC2OutputDevice clock generator circuit connection pins.	29	37	A-Z	Input	Integrator amplifier input. To be connected to auto-zero capacitor.
3139IN HIdesignators are for reference and do not imply that LO should be connected to lower potential, e.g., for negative inputs IN LO has a higher potential than IN HI.3240COMMONSupply/ OutputInternal voltage reference output.3341CREF- CREF+Connection pins for reference capacitor.3442CREF+Connection pins for reference voltage to the device. REF HI should be positive reference to REF LO.3543REF LO REF HIInput373TESTInput384OSC3 OutputOutput396OSC2 OutputDevice clock generator circuit connection pins.	30	38	IN LO	Input	Differential inputs. To be connected to input voltage to be measured. LO and HI
Image: specific constraint of the specific c	31	39	IN HI	-	designators are for reference and do not imply that LO should be connected to lower
32 40 COMMON Supply/ Output Internal voltage reference output. 33 41 C _{REF} - (C _{REF} + Connection pins for reference capacitor. 34 42 C _{REF} + Connection pins for reference voltage to the device. REF HI should be positive reference to REF LO. 35 43 REF LO Input Input pins for reference voltage to the device. REF HI should be positive reference to REF LO. 37 3 TEST Input Display test. Turns on all segments when tied to V+. 38 4 OSC3 Output Device clock generator circuit connection pins. 39 6 OSC2 Output Device clock generator circuit connection pins.					potential, e.g., for negative inputs IN LO has a higher potential than IN HI.
33 41 C _{REF} - Connection pins for reference capacitor. 34 42 C _{REF} + Connection pins for reference capacitor. 35 43 REF LO Input Input pins for reference voltage to the device. REF HI should be positive reference to REF LO. 36 44 REF HI Display test. Turns on all segments when tied to V+. 38 4 OSC3 Output 39 6 OSC2 Output 40 7 OSC1 Input	32	40	COMMON	Supply/ Output	Internal voltage reference output.
34 42 C _{REF} + 35 43 REF LO Input Input pins for reference voltage to the device. REF HI should be positive reference to REF LO. 36 44 REF HI Input Display test. Turns on all segments when tied to V+. 37 3 TEST Input Display test. Turns on all segments when tied to V+. 38 4 OSC3 Output Device clock generator circuit connection pins. 39 6 OSC2 Output Device clock generator circuit connection pins.	33	41	C _{REF} -		Connection pins for reference capacitor.
3543REF LOInputInput pins for reference voltage to the device. REF HI should be positive reference to REF LO.3644REF HIInputInput pins for reference voltage to the device. REF HI should be positive reference to REF LO.373TESTInputDisplay test. Turns on all segments when tied to V+.384OSC3OutputDevice clock generator circuit connection pins.396OSC2Output407OSC1Input	34	42	C _{REF} +		
36 44 REF HI REF LO. 37 3 TEST Input Display test. Turns on all segments when tied to V+. 38 4 OSC3 Output Device clock generator circuit connection pins. 39 6 OSC2 Output 40 7 OSC1 Input	35	43	REF LO	Input	Input pins for reference voltage to the device. REF HI should be positive reference to
37 3 TEST Input Display test. Turns on all segments when tied to V+. 38 4 OSC3 Output Device clock generator circuit connection pins. 39 6 OSC2 Output 40 7 OSC1 Input	36	44	REF HI		REF LO.
38 4 OSC3 Output Device clock generator circuit connection pins. 39 6 OSC2 Output 40 7 OSC1 Input	37	3	TEST	Input	Display test. Turns on all segments when tied to V+.
40 7 OSC1 Input	38	4	OSC3	Output	Device clock generator circuit connection pins.
	40	7	0302	Input	

Detailed Description

Analog Section

Figure 2 shows the Analog Section for the ICL7136. Each measurement cycle is divided into four phases. They are (1) auto-zero (A-Z), (2) signal integrate (INT) and (3) de-integrate (DE), (4) zero integrate (ZI).

Auto-Zero Phase

During auto-zero three things happen. First, input high and low are disconnected from the pins and internally shorted to analog

COMMON. Second, the reference capacitor is charged to the reference voltage. Third, a feedback loop is closed around the system to charge the auto-zero capacitor C_{AZ} to compensate for offset voltages in the buffer amplifier, integrator, and comparator. Since the comparator is included in the loop, the A-Z accuracy is limited only by the noise of the system. In any case, the offset referred to the input is less than 10μ V.

Signal Integrate Phase

During signal integrate, the auto-zero loop is opened, the internal short is removed, and the internal input high and low

are connected to the external pins. The converter then integrates the differential voltage between IN HI and IN LO for a fixed time. This differential voltage can be within a wide common mode range: up to 1V from either supply. If, on the other hand, the input signal has no return with respect to the converter power supply, IN LO can be tied to analog COMMON to establish the correct common mode voltage. At the end of this phase, the polarity of the integrated signal is determined.

De-Integrate Phase

The final phase is de-integrate, or reference integrate. Input low is internally connected to analog COMMON and input high is connected across the previously charged reference capacitor. Circuitry within the chip ensures that the capacitor will be connected with the correct polarity to cause the integrator output to return to zero. The time required for the output to return to zero is proportional to the input signal. Specifically the digital reading displayed is:

DISPLAY READING =
$$1000 \left(\frac{V_{IN}}{V_{REF}} \right)$$
.

Zero Integrator Phase

The final phase is zero integrator. First, input low is shorted to analog COMMON. Second, the reference capacitor is charged to the reference voltage. Finally, a feedback loop is closed around the system to IN HI to cause the integrator output to return to zero. Under normal conditions, this phase lasts for between 11 to 140 clock pulses, but after a "heavy" overrange conversion, it is extended to 740 clock pulses.

Differential Input

The input can accept differential voltages anywhere within the common mode range of the input amplifier, or specifically from 0.5V below the positive supply to 1V above the negative supply. In this range, the system has a CMRR of 86dB typical. However, care must be exercised to assure the integrator output does not saturate. A worst case condition would be a large positive common mode voltage with a near full scale negative differential input voltage. The negative input signal drives the integrator positive when most of its swing has been used up by the positive common mode voltage. For these critical applications the integrator output swing can be reduced to less than the recommended 2V full scale swing with little loss of accuracy. The integrator output can swing to within 0.3V of either supply without loss of linearity.

Differential Reference

The reference voltage can be generated anywhere within the power supply voltage of the converter. The main source of common mode error is a roll-over voltage caused by the reference capacitor losing or gaining charge to stray capacity on its nodes. If there is a large common mode voltage, the reference capacitor can gain charge (increase voltage) when called up to de-integrate a positive signal but lose charge (decrease voltage) when called up to deintegrate a negative input signal. This difference in reference for positive or negative input voltage will give a roll-over error. However, by selecting the reference capacitor such that it is large enough in comparison to the stray capacitance, this error can be held to less than 0.5 count worst case. (See Component Value Selection.)



FIGURE 2. ANALOG SECTION OF ICL7136

7

Analog COMMON

This pin is included primarily to set the common mode voltage for battery operation or for any system where the input signals are floating with respect to the power supply. The COMMON pin sets a voltage that is approximately 2.8V more negative than the positive supply. This is selected to give a minimum end-of-life battery voltage of about 6.8V. However, analog COMMON has some of the attributes of a reference voltage. When the total supply voltage is large enough to cause the zener to regulate (>7V), the COMMON voltage will have a low voltage coefficient (0.001%/V), low output impedance ($\cong 15\Omega$), and a temperature coefficient typically less than 150ppm/^OC.

The limitations of the on chip reference should also be recognized, however. Due to their higher thermal resistance, plastic parts are poorer in this respect than ceramic. The combination of reference Temperature Coefficient (TC), internal chip dissipation, and package thermal resistance can increase noise near full scale from $25\mu V$ to $80\mu V_{P-P}$. Also the linearity in going from a high dissipation count such as 1000 (20 segments on) to a low dissipation count such as 1111 (8 segments on) can suffer by a count or more. Devices with a positive TC reference may require several counts to pull out of an over range condition. This is because over-range is a low dissipation mode, with the three least significant digits blanked. Similarly, units with a negative TC may cycle between over range and a non-over range count as the die alternately heats and cools. All these problems are of course eliminated if an external reference is used.

The ICL7136, with its negligible dissipation, suffers from none of these problems. In either case, an external reference can easily be added, as shown in Figure 3.

Analog COMMON is also used as the input low return during auto-zero and de-integrate. If IN LO is different from analog COMMON, a common mode voltage exists in the system and is taken care of by the excellent CMRR of the converter. However, in some applications IN LO will be set at a fixed known voltage (power supply common for instance). In this application, analog COMMON should be tied to the same point, thus removing the common mode voltage from the converter. The same holds true for the reference voltage. If reference can be conveniently tied to analog COMMON, it should be since this removes the common mode voltage from the reference system.

Within the IC, analog COMMON is tied to an N-Channel FET that can sink approximately 3mA of current to hold the voltage 2.8V below the positive supply (when a load is trying to pull the common line positive). However, there is only 10μ A of source current, so COMMON may easily be tied to a more negative voltage thus overriding the internal reference.



FIGURE 3B. FIGURE 3. USING AN EXTERNAL REFERENCE

TEST

The TEST pin serves two functions. On the ICL7136 it is coupled to the internally generated digital supply through a 500Ω resistor. Thus it can be used as the negative supply for externally generated segment drivers such as decimal points or any other presentation the user may want to include on the LCD display. Figures 4 and 5 show such an application. No more than a 1mA load should be applied.



FIGURE 4. SIMPLE INVERTER FOR FIXED DECIMAL POINT

The second function is a "lamp test". When TEST is pulled high (to V+) all segments will be turned on and the display should read "-1888". The TEST pin will sink about 5mA under these conditions.

CAUTION: On the ICL7136, in the lamp test mode, the segments have a constant DC voltage (no square-wave) and may burn the LCD display if left in this mode for several minutes.



FIGURE 5. EXCLUSIVE "OR" GATE FOR DECIMAL POINT DRIVE

Digital Section

Figures 6 shows the digital section for the ICL7136. In the ICL7136, an internal digital ground is generated from a 6V Zener diode and a large P-Channel source follower. This supply is made stiff to absorb the relatively large capacitive currents when the back plane (BP) voltage is switched. The BP frequency is the clock frequency divided by 800. For three readings/second this is a 60Hz square wave with a nominal amplitude of 5V. The segments are driven at the same frequency and amplitude and are in phase with BP when OFF, but out of phase when ON. In all cases negligible DC voltage exists across the segments.

The polarity indication is "on" for negative analog inputs. If IN LO and IN HI are reversed, this indication can be reversed also, if desired.



FIGURE 6. ICL7136 DIGITAL SECTION

System Timing

Figure 7 shows the clocking arrangement used in the ICL7136. Two basic clocking arrangements can be used:

- 1. Figure 9A, an external oscillator connected to DIP pin 40.
- 2. Figure 9B, an R-C oscillator using all three pins.

The oscillator frequency is divided by four before it clocks the decade counters. It is then further divided to form the three convert-cycle phases. These are signal integrate (1000 counts), reference de-integrate (0 to 2000 counts) and auto-zero (1000 to 3000 counts). For signals less than full scale, auto-zero gets the unused portion of reference deintegrate. This makes a complete measure cycle of 4,000 counts (16,000 clock pulses) independent of input voltage. For three readings/second, an oscillator frequency of 48kHz would be used.

To achieve maximum rejection of 60Hz pickup, the signal integrate cycle should be a multiple of 60Hz. Oscillator frequencies of 240kHz, 120kHz, 80kHz, 60kHz, 48kHz, 40kHz, $33^{1}/_{3}$ kHz, etc., should be selected. For 50Hz rejection, Oscillator frequencies of 200kHz, 100kHz, $66^{2}/_{3}$ kHz, 50kHz, 40kHz, etc. would be suitable. Note that 40kHz (2.5 readings/sec.) will reject both 50Hz and 60Hz (also 400Hz and 440Hz).





FIGURE 7B. RC OSCILLATOR FIGURE 7. CLOCK CIRCUITS

Component Value Selection

Integrating Resistor

Both the buffer amplifier and the integrator have a class A output stage with 100 μ A of quiescent current. They can supply 1 μ A of drive current with negligible nonlinearity. The integrating resistor should be large enough to remain in this very linear region over the input voltage range, but small enough that undue leakage requirements are not placed on the PC board. For 2V full scale, 1.8M Ω is near optimum and similarly a 180k Ω for a 200mV scale.

Integrating Capacitor

The integrating capacitor should be selected to give the maximum voltage swing that ensures tolerance buildup will not saturate the integrator swing (approximately 0.3V from either supply). In the ICL7136, when the analog COMMON is used as a reference, a nominal +2V full-scale integrator swing is fine. For three readings/second (48kHz clock) nominal values for C_{INT} are 0.047 μ F and 0.5 μ F, respectively. Of course, if different oscillator frequencies are used, these values should be changed in inverse proportion to maintain the same output swing.

An additional requirement of the integrating capacitor is that it must have a low dielectric absorption to prevent roll-over errors. While other types of capacitors are adequate for this application, polypropylene capacitors give undetectable errors at reasonable cost.

Auto-Zero Capacitor

The size of the auto-zero capacitor has some influence on the noise of the system. For 200mV full scale where noise is very important, a $0.47\mu F$ capacitor is recommended. On the 2V scale, a $0.047\mu F$ capacitor increases the speed of recovery from overload and is adequate for noise on this scale.

Reference Capacitor

A 0.1µF capacitor gives good results in most applications. However, where a large common mode voltage exists (i.e., the REF LO pin is not at analog COMMON) and a 200mV scale is used, a larger value is required to prevent roll-over error. Generally 1µF will hold the roll-over error to 0.5 count in this instance.

Oscillator Components

For all ranges of frequency a $180k\Omega$ resistor is recommended and the capacitor is selected from the equation:

$$f = \frac{0.45}{RC}$$
 For 48kHz Clock (3 Readings/s.),

C = 50 p F.

Reference Voltage

The analog input required to generate full scale output (2000 counts) is: V_{IN} = 2V_{REF}. Thus, for the 200mV and 2V scale, V_{RFF} should equal 100mV and 1V, respectively. However, in many applications where the A/D is connected to a transducer, there will exist a scale factor other than unity between the input voltage and the digital reading. For instance, in a weighing system, the designer might like to have a full scale reading when the voltage from the transducer is 0.662V. Instead of dividing the input down to 200mV, the designer should use the input voltage directly and select V_{RFF} = 0.341V. Suitable values for integrating resistor and capacitor would be 330 k\Omega and 0.047 $\mu\text{F}.$ This makes the system slightly guieter and also avoids a divider network on the input. Another advantage of this system occurs when a digital reading of zero is desired for $V_{IN} \neq 0$. Temperature and weighing systems with a variable fare are examples. This offset reading can be conveniently generated by connecting the voltage transducer between IN HI and COMMON and the variable (or fixed) offset voltage between COMMON and IN LO.



Values shown are for 200mV full scale, 3 readings/sec., floating supply voltage (9V battery).

FIGURE 8. ICL7136 USING THE INTERNAL REFERENCE

Typical Applications

The ICL7136 may be used in a wide variety of configurations. The circuits which follow show some of the possibilities, and serve to illustrate the exceptional versatility of these A/D converters.

The following application notes contain very useful information on understanding and applying this part and are available from Intersil.

Application Notes

NOTE #	DESCRIPTION
AN016	"Selecting A/D Converters"
AN017	"The Integrating A/D Converter"
AN018	"Do's and Don'ts of Applying A/D Converters"
AN023	"Low Cost Digital Panel Meter Designs"
AN032	"Understanding the Auto-Zero and Common Mode Performance of the ICL7136/7/9 Family"
AN046	"Building a Battery-Operated Auto Ranging DVM with the ICL7106"
AN052	"Tips for Using Single Chip 3 ¹ / ₂ Digit A/D Converters"



FIGURE 9. RECOMMENDED COMPONENT VALUES FOR 2V FULL SCALE



A silicon diode-connected transistor has a temperature coefficient of about $-2mV/^{O}C$. Calibration is achieved by placing the sensing transistor in ice water and adjusting the zeroing potentiometer for a 000.0 reading. The sensor should then be placed in boiling water and the scale-factor potentiometer adjusted for a 100.0 reading. † Value depends on clock frequency.





FIGURE 11. CIRCUIT FOR DEVELOPING UNDERRANGE AND OVERRANGE SIGNAL FROM ICL7136 OUTPUTS



Test is used as a common-mode reference level to ensure compatibility with most op amps.

FIGURE 12. AC TO DC CONVERTER WITH ICL7136

Die Characteristics

DIE DIMENSIONS:

127 mils x 149 mils

METALLIZATION:

Type: Al Thickness: 10kÅ ±1kÅ

Metallization Mask Layout

ICL7136 D_2 E₂ F_2 B₂ C_2 E₁ G_1 F₁ A_1 A₂ (14) (13) (12) (11) (10) (9) (8) (7) (6) (5) D₃ (15) (4) B₁ (53) | <u>s</u> sir B₃ (16) (3) C₁ F₃ (17) 和地 E₃ (18) (2) D₁ AB₄ (19) (1) V+ POL (20) (40) OSC 1 **BP/GND (21)** 而为 G₃ (22) **1**1 A₃ (23) (39) OSC 2 C₃ (24) G₂ (25) (38) OSC 3 (37) TEST . 112]| V- (26) HOUDLD (27) (28) (30) (31) (33) (36) (29) (32) (34) (35) CREF- CREF+ INT BUFF A/Z IN LO IN HI COMM LO ΗΙ

PASSIVATION:

Type: PSG Nitride Thickness: 15kÅ ±3kÅ

REF

REF

Dual-In-Line Plastic Packages (PDIP)



NOTES:

- 1. Controlling Dimensions: INCH. In case of conflict between English and Metric dimensions, the inch dimensions control.
- 2. Dimensioning and tolerancing per ANSI Y14.5M-1982.
- 3. Symbols are defined in the "MO Series Symbol List" in Section 2.2 of Publication No. 95.
- 4. Dimensions A, A1 and L are measured with the package seated in JEDEC seating plane gauge GS-3.
- D, D1, and E1 dimensions do not include mold flash or protrusions. Mold flash or protrusions shall not exceed 0.010 inch (0.25mm).
- E and e_A are measured with the leads constrained to be perpendicular to datum -C-.
- 7. e_B and e_C are measured at the lead tips with the leads unconstrained. e_C must be zero or greater.
- 8. B1 maximum dimensions do not include dambar protrusions. Dambar protrusions shall not exceed 0.010 inch (0.25mm).
- 9. N is the maximum number of terminal positions.
- 10. Corner leads (1, N, N/2 and N/2 + 1) for E8.3, E16.3, E18.3, E28.3, E42.6 will have a B1 dimension of 0.030 0.045 inch (0.76 1.14mm).

E40.6 (JEDEC MS-011-AC ISSUE B) 40 LEAD DUAL-IN-LINE PLASTIC PACKAGE

	INC	HES	MILLIM		
SYMBOL	MIN	MAX	MIN	MAX	NOTES
Α	-	0.250	-	6.35	4
A1	0.015	-	0.39	-	4
A2	0.125	0.195	3.18	4.95	-
В	0.014	0.022	0.356	0.558	-
B1	0.030	0.070	0.77	1.77	8
С	0.008	0.015	0.204	0.381	-
D	1.980	2.095	50.3	53.2	5
D1	0.005	-	0.13	-	5
E	0.600	0.625	15.24	15.87	6
E1	0.485	0.580	12.32	14.73	5
е	0.100 BSC		2.54 BSC		-
e _A	0.600 BSC		15.24 BSC		6
e _B	-	0.700	-	17.78	7
L	0.115	0.200	2.93	5.08	4
Ν	40		4	0	9

Rev. 0 12/93

Metric Plastic Quad Flatpack Packages (MQFP)



Q44.10x10 (JEDEC MS-022AB ISSUE B) 44 LEAD METRIC PLASTIC QUAD FLATPACK PACKAGE

	INCHES		MILLIMETERS		
SYMBOL	MIN	MAX	MIN	MAX	NOTES
А	-	0.096	-	2.45	-
A1	0.004	0.010	0.10	0.25	-
A2	0.077	0.083	1.95	2.10	-
b	0.012	0.018	0.30	0.45	6
b1	0.012	0.016	0.30	0.40	-
D	0.515	0.524	13.08	13.32	3
D1	0.389	0.399	9.88	10.12	4, 5
E	0.516	0.523	13.10	13.30	3
E1	0.390	0.398	9.90	10.10	4, 5
L	0.029	0.040	0.73	1.03	-
Ν	44		4	14	7
е	0.032 BSC		0.80 BSC		-

NOTES:

- 1. Controlling dimension: MILLIMETER. Converted inch dimensions are not necessarily exact.
- 2. All dimensions and tolerances per ANSI Y14.5M-1982.
- 3. Dimensions D and E to be determined at seating plane -C-
- Dimensions D1 and E1 to be determined at datum plane

 -H .
- 5. Dimensions D1 and E1 do not include mold protrusion. Allowable protrusion is 0.25mm (0.010 inch) per side.
- 6. Dimension b does not include dambar protrusion. Allowable dambar protrusion shall be 0.08mm (0.003 inch) total.
- 7. "N" is the number of terminal positions.

All Intersil U.S. products are manufactured, assembled and tested utilizing ISO9000 quality systems. Intersil Corporation's quality certifications can be viewed at www.intersil.com/design/quality

Intersil products are sold by description only. Intersil Corporation reserves the right to make changes in circuit design, software and/or specifications at any time without notice. Accordingly, the reader is cautioned to verify that data sheets are current before placing orders. Information furnished by Intersil is believed to be accurate and reliable. However, no responsibility is assumed by Intersil or its subsidiaries for its use; nor for any infringements of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of Intersil or its subsidiaries.

For information regarding Intersil Corporation and its products, see www.intersil.com

Rev. 2 4/99